

This whitepaper provides a complete list of IP addresses and ports required to enable Inner Range products to communicate to a Multipath-IP enabled central station.

T4000

Required:

UDP inbound and outbound Multipath Communications

52.243.72.107 : 41001

13.70.105.118 : 41001

203.34.170.226 : 41001

58.108.221.52 : 41001

SkyTunnel Communications & Upload/Download

TCP inbound and outbound

23.101.229.107 : 40844

Essential:

Firmware Update Server

TCP inbound and outbound

52.243.72.107 : 50000

T4000 Review Server

TCP inbound and outbound

52.243.72.107 : 50001

SkyTunnel Devices - Inception, Integriti IAC, Integriti ISC, Infiniti

SkyTunnel Communications

TCP inbound and outbound

23.101.229.107 : 40844

skytunnel.com.au : 40844

Please Note:

Inner Range will endeavour keep the Public Multipath-IP IP addresses the same, however they may be changed if required. For this reason it is not recommended that firewall rules are locked to destination IP's.